

Radio Commands

STATION TUNING

Starting a dialogue

Hold the voice control button on the multi-functional steering wheel until the listening beep is heard. Any audio sources in the vehicle are muted.

Radio stations

Frequencies are said as in the following examples:

In place of **Tune**, you can use the command **Select**.

Tuning to a radio station

You say	System response	Message centre display
<i>Radio play</i>	Radio play	RADIO PLAY
<i>Radio tune preset one (two, three, etc.)</i>	Radio tunes to preset 1 (2, 3 etc.)	RADIO PRESET 1 (2, 3, etc.)

Radio Commands

STORING RADIO STATIONS

Storing via voice command

Once you have tuned to a Radio station, it is possible to store that station for future use as a preset.

The command **Radio store preset** <say number> (1-9), calls up the dialogue for storing a preset station.

The command **Radio band autostore**, enters the autostore function for the selected frequency band (e.g. FM).

Name tags

Name tags are a unique name or phrase of your choice, which can be used to recall a radio station. The name tags used can be the station name or a completely separate name of your choosing.

The names are stored in a directory by using the **Radio store name** command. The system responds with “Name please”. You the say the name that you have chosen (e.g. Radio 1).

The system will read out a list of current name tags when given the command **Radio play directory**.

Radio tune <name tag> is used to select a station that has been previously stored.

Storing via voice command

You say	System response	Message centre display
Radio store preset <preset number> (1-9)	Radio store preset <preset number>	RADIO STORE PRESET (1-9).
(1) Radio store name.....(3) <name>	(2) Radio store name.....<name><frequency>	RADIO STORE NAME,NAME PLEASE.
Radio autostore	Radio autostore	RADIO AUTOSTORE

Radio Commands

RADIO PLAY DIRECTORY

Tune/delete from the radio directory

The command **Radio play directory** enables you to have all your radio name tag entries in your voice recognition radio directory, read out in stored order.

Commands can be entered during the system response.

Replay

After a name tag has been read out by the system, give the command **Replay** and the name tag will be repeated.

Tune

After a name tag has been read out by the system, give the command **Tune** and the radio tunes to the station saved under that name tag.

Delete

After a name tag has been read out by the system, give the command **Delete** and the name tag will be removed from the directory.

Cancel

After a name tag has been read out by the system, give the command **Cancel** and the current voice session will end.

Tuning from the radio directory

You say	System response	Message centre display
Radio play directory	Radio play directory. The system reads out radio directory entries. You can say Replay , Tune , Delete or Cancel after each entry. The system will carry out the command for the last spoken entry.	RADIO DIRECTORY <Station frequency>

Radio Commands

RADIO DELETE DIRECTORY

Deleting the directory

The command **Radio delete directory** deletes all entries in the radio directory.

Deleting the radio directory

You say	System response	Message centre display
1. Radio delete directory	1. Radio delete directory confirm yes or no	1. DELETE DIRECTORY SAY YES OR NO
2. Yes	2. Are you sure you want to delete the whole directory?	2. SAY YES OR NO
3. Yes	3. Directory deleted	3. DIRECTORY DELETED